PHILIPS

CoreLine waterproof

WT120C G3/WT121C G3

Scan me! DOWNLOAD

PSU/PSD
PSU-TW3 /PSD-TW3
- Triangle hook 2x
- Installation bracket 2x
- Gland cable ring 2x
- Bolt M3X40 2x
- Nut M3 2x
- Seal ring 2x
- Gland PG13.5 1x

WEC3/WEC3 TW1
- Triangle hook 2x
- Installation bracket 2x
- Black gas stick 1x (1x (TW1))
- Bolt M3X40 2x
- Nut M3 2x
- Seal ring 2x
- Gland cable 7 ~ 2x (TW1)

Scan me! DOWNLOAD

PSU/PSD TW3 / WEC3/WEC3 TW1

220V 240V 50Hz 60Hz

No flicker / No stroboscopic effect

IP66 IK08

PSU/PSU TW3

	Power	Lumen	Energy efficiency label of Light source	Emergency option	Emergency Delivered	Max. mounting height
WT120C G3 20S/840 PSU L600	13	2000	C	Yes	0.75	*
WT120C G3 40S/840 PSU L600	26	4000	C	No	0.75	*
WT120C G3 27S/840 PSU L1200	17	2700	C	Yes	1.24	*
WT120C G3 40S/840 PSU L1200	25	4000	C	Yes	1.24	*
WT120C G3 60S/840 PSU L1200	37.5	6000	C	Yes	1.24	*
WT120C G3 50S/840 PSU L1500	30	5000	C	Yes	1.29	*
WT120C G3 40S/830 PSU L1200	25	3800	C	Yes	1.24	*
WT120C G3 60S/865 PSU L1200	25	4850	C	Yes	1.24	*
WT121C G3 60S/840 PSU L1200	25	3800	C	Yes	1.24	*
WT121C G3 60S/865 PSU L1200	21.5	3400	C	Yes	1.00	*
WT121C G3 50S/840 PSU L1500	37.5	6000	C	Yes	1.55	*
WT121C G3 50S/865 PSU L1500	30	5000	C	Yes	1.55	*
WT120C G3 100S/840 PSU L1500	62.5	10000	C	Yes	1.55	*
WT120C G3 120S/840 PSU L1500	75	12000	C	Yes	1.60	*
WT120C G3 60S/830 PSU L1500	37.5	3800	C	Yes	1.55	*
WT120C G3 34S/865 PSU L1500	21.5	3400	C	Yes	1.55	*
WT120C G3 60S/865 PSU L1500	37.5	6000	C	Yes	1.55	*
WT120C G3 40S/840 HE PSU L1500	33.5	4200	B	Yes	1.28	*
WT120C G3 80S/840 HE PSU L1500	50	6000	B	Yes	1.55	*
WT120C G3 160S/840 HE PSU L1500	75	14000	B	Yes	1.60	*
WT120C G3 24_29_35_40S/840 PSU L600	14 W 8 W	2400/2800/3200/4000 lm	C	No	0.75	*
WT120C G3 27_33_39_46S/840 PSU L1200	17 W 8 W	2700/3300/3900/4600 lm	C	Yes	1.24	*
WT120C G3 27_33_39_46S/840 PSU L1200	17 W 8 W	2700/3300/3900/4600 lm	C	Yes	1.24	*
WT120C G3 27_33_39_46S/840 PSU L1200	34 W 8 W	2700/3300/3900/4600 lm	C	Yes	1.24	*
WT121C G3 27_33_39_46S/840 PSU L1200	34 W 8 W	2700/3300/3900/4600 lm	C	Yes	1.24	*
WT120C G3 35_43_51_60S/830 PSU L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.55	*
WT120C G3 35_43_51_60S/840 PSU L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.55	*
WT120C G3 35_43_51_60S/865 PSU L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.55	*
WT121C G3 35_43_51_60S/840 PSU L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.55	*
WT120C G3 35_43_51_60S/830_40 PSU TW3 L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.55	*
WT120C G3 70_86_100_120S/840 PSU L1500	42 W 8 W	6800/8000/9200/10800 lm	C	Yes	1.60	*
WT120C G3 70_86_100_120S/830_40 PSU TW3 L1500	42 W 8 W	6800/8000/9200/10800 lm	C	Yes	1.60	*
WT120C G3 27_33_39_46S/830_40 PSU TW3 L1200	17	2700	C	Yes	1.24	*
WT120C G3 27_33_39_46S/840 TW3 PSU L1200	17	2700/3300/3900/4600	C	Yes	1.40	75
WT120C G3 35_43_51_60S/830_40 PSU TW3 L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.40	65
WT120C G3 40S/840 PSU TW3 L1200	25	4000	C	Yes	1.24	*
WT120C G3 34S/840 PSU TW3 L1500	21.5	3400	C	Yes	1.76	61
WT120C G3 35_43_51_60S/840_40 PSU TW3 L1500	21 W 8 W	3400/4000/4600/5400 lm	C	Yes	1.76	58
WT120C G3 46_57_69_80S/840 PSU TW3 L1500	29 W 8 W	4600/5700/6900/8000 lm	C	Yes	1.76	27
WT120C G3 60S/840 PSU TW3 L1500	37.5	6000	C	Yes	1.76	35
WT120C G3 60S/865 PSU TW3 L1500	30	6000	C	Yes	1.76	27
WT120C G3 20S/840 PSU POC L600	13	1900	C	No	0.75	*
WT120C G3 27S/840 PSU POC L1200	17	2700	C	Yes	1.24	*
WT120C G3 40S/840 PSU POC L1200	25	3700	C	Yes	1.24	*
WT120C G3 34S/840 PSU POC L1500	21.5	3200	C	Yes	1.55	*
WT120C G3 60S/840 PSU POC L1500	37.5	5800	C	Yes	1.55	*
WT120C G3 50S/840 PSU POC L1500	30	7600	C	Yes	1.55	*


▲ 3000K lumen output is 3.5% lower than 4000K.

© 09/2026 Signify Holding. All rights reserved

Data subject to change without notice.
Keep for future reference: www.philips.com/lighting

WEC3/WEC3 TW1

WEC3




WEC3 TW1



Type	Dimension (mm)							Nr of clips
	A	B	C	D	E min	E max	F	
WT120C G3 WEC3 L1200	1240	76	80	38	538	1062	85	10
WT120C G3 WEC3 L1500	1540				838	1362		12

Type	Dimension (mm)							Nr of clips
	A	B	C	D	E min	E max	F	
WT120C G3 WEC3 TW1 L1200	1295	76	80	38	538	1062	85	10
WT120C G3 WEC3 TW1 L1500	1585				838	1362		12

1



1a



1b



1c



PSD/PSD TW1/TW3

	Power	Lumen	Energy efficiency label of Light source	Emergency option	Emergency Delivered	Max. mounting height
WT120C G3 40S/840 PSD L600	25	4000	C	No	0.90	*
WT120C G3 60S/840 PSD L1200	37.5	6000	C	Yes	1.70	*
WT120C G3 50S/840 PSD L1200	30	6000	C	Yes	1.37	*
WT120C G3 50S/840 PSD L1500	50	8000	C	Yes	1.71	*
WT120C G3 100S/840 PSD L1500	62.5	12000	C	Yes	1.92	53
WT120C G3 80S/840 HE PSD L1500	40	6000	B	Yes	1.37	*
WT120C G3 160S/840 HE PSD L1500	75	14000	B	Yes	1.71	*
WT120C G3 60S/840 PSD TW1 L600	37.5	6000	C	Yes	1.92	35
WT120C G3 60S/840 PSD TW1 L1200	25	4000	C	Yes	1.54	53
WT120C G3 60S/840 PSD TW1 L1500	30	6000	C	Yes	1.54	27
WT120C G3 60S/840 PSD TW3 L1500	37.5	6000	C	Yes	1.92	35
WT120C G3 80S/840 PSD TW3 L1500	50	8000	C	Yes	1.92	27

*Refer to the datasheet for detailed information on through wiring options.

1d



1e




PSU/PSD




Type	Dimension (mm)							Nr of clips
	A	B	C	D	E min	E max	F	
WT120C G3 L600	665	76	80	38	308	512	85	6
WT120C G3 L1200	1215				538	1062		10
WT120C G3 L1500	1515				838	1362		12

PSU TW3/PSD TW1 /PSD TW3




Type	Dimension (mm)							Nr of clips
	A	B	C	D	E min	E max	F	
WT120C G3 TW3/TW1 L600	665	76	80	38	308	512	85	6
WT120C G3 TW3 L1200	1235				538	1062		10
WT120C G3 TW3 L1500	1535				838	1362		12

2a PSU/PSU TW3



PSD TW1



PSD/PSD TW3




Note: "M1" & "M2" for multifunctional terminal interface, such as for TW1/TW3 connection, for emergency unit connection.

2b WEC3/WEC3 TW1









Through wiring (optional)




(*) NYM cable is suitable for TW

PSU TW1

Through wiring with TW accessory (optional)

Insert the terminal block with through wires



12NC	Description	EOC
911401816587	WT120Z TW-5x2.5-L600 10PCS	872019755116499
911401816787	WT120Z TW-3x2.5-L1200 10PCS	872019755117899
911401816987	WT120Z TW-3x2.5-L1500 10PCS	872019755119299


PSU TW3

Insert the terminal block with through wires

12NC	Description	EOC
911401816587	WT120Z TW-5x2.5-L600 10PCS	872019755116499
911401816787	WT120Z TW-3x2.5-L1200 10PCS	872019755117899
911401816987	WT120Z TW-3x2.5-L1500 10PCS	872019755119299
911401817087	WT120Z TW-5x2.5-L1500 10PCS	872019755120899

PSD TW1(L600)

Insert the terminal block with through wires



12NC	Description	EOC
911401816687	WT120Z TW-5x2.5-L600 10PCS	872019755116199

PSD TW1(L1200 L1500)

Insert the terminal block with through wires

12NC	Description	EOC
911401883288	WT120Z TW-2x2.5-L1200 10PCS	872110349088899
911401816787	WT120Z TW-3x2.5-L1200 10PCS	872019755117899
911401883388	WT120Z TW-2x2.5-L1500 10PCS	872110349089599
911401816987	WT120Z TW-3x2.5-L1500 10PCS	872019755119299

PSD TW3

Insert the terminal block with through wires



Additional Through wiring options:		
12NC	Description	EOC
911401883288	WT120Z TW-2x2.5-L1200 10PCS	872110349088899
911401883388	WT120Z TW-2x2.5-L1500 10PCS	872110349089599
911401817087	WT120Z TW-5x2.5-L1500 10PCS	872019755120899

3 Mid-or side-entry(optional) Knock out for cable entry



WEC3/WEC3 TW1



4 PSU/PSD Replacement of Silicone Plug(optional)





5

6

7

CCT switch option

Refer to datasheet for detailed information on wattage and lumen output.

WT120C G3 27_33_39_46S/830_40 PSU TW3 L1200	
WT120C G3 35_43_51_60S/830_40 PSU TW3 L1500	



Lumen switch option

Refer to datasheet for detailed information on wattage and lumen output.

WT120C G3 27_33_39_46S/830 PSU L1200
WT121C G3 27_33_39_46S/840 PSU L1200
WT120C G3 27_33_39_46S/840 PSU L1200
WT120C G3 27_33_39_46S/865 PSU L1200
WT120C G3 27_33_39_46S/840 TW3 PSU L1200
WT120C G3 27_33_39_46S/830_40 PSU TW3 L1200

Pin 1	Pin 2	27_33_39_46S
ON	ON	27S
ON	OFF	33S
OFF	ON	39S
OFF	OFF	46S(Default)



WT120C G3 35_43_51_60S/830 PSU L1500
WT120C G3 35_43_51_60S/840 PSU L1500
WT120C G3 35_43_51_60S/865 PSU L1500
WT121C G3 35_43_51_60S/840 PSU L1500
WT120C G3 35_43_51_60S/830_40 PSU TW3 L1500

Pin 1	Pin 2	35_43_51_60S
ON	ON	35S
ON	OFF	43S
OFF	ON	51S
OFF	OFF	60S(Default)

WT120C G3 70_86_100_120S/840 PSU L1500

Pin 1	Pin 2	70_86_100_120S
ON	ON	70S
ON	OFF	86S
OFF	ON	100S
OFF	OFF	120S(Default)



WT120C G3 24_29_35_40S/840 PSU L600
WT120C G3 24_29_35_40S/840 PSU TW3 L600

Pin 1	Pin 2	24_29_35_40S
ON	ON	24S
ON	OFF	29S
OFF	ON	35S
OFF	OFF	40S(Default)

WT120C G3 46_57_69_80S/840 PSU L1500
WT120C G3 46_57_69_80S/840 PSU TW3 L1500

Pin 1	Pin 2	46_57_69_80S
ON	ON	46S
ON	OFF	57S
OFF	ON	69S
OFF	OFF	80S(Default)



8

Installation of Emergency unit

(option with additional emergency module EM300V)
Emergency Module:
Follow manual instruction of EM300V
Order Code
912401483668 EM300V ELB_P3 kit HV 6.4V 2000mAh LFP v2
The emergency pack is not provided.





Charge time



Emergency wiring







Rated lumen output in emergency mode when using EL kit EM300V: min 400lm



	405 PSU	603 PSU	805 PSU	805 UI PSU	1205 PSU	1205 UI PSU
Driver I peak[A]	23.1	23.1	25.1	25.1	25	
Driver Turf [cm]	221	221	214	214	230	

	405 PSU	603 PSU	805 PSU	805 UI PSU	1205 PSU
MCB 10A type B	22	22	21	21	20
MCB 10A type C	34	34	33	33	31
MCB 10A type D	37	37	36	36	34
MCB 16A type B	36	36	35	35	33
MCB 16A type C	57	57	56	56	53
MCB 16A type D	62	62	60	60	57


For PSD product series, rated light output in DC emergency mode:
The luminaire is working on 110V-277V AC/DC. Luminous flux by 220-240V DC supply.
Refer to datasheet for detailed specification information.

- Do not stare into LED light beam.
- The luminaire shall be installed by a qualified electrician and wired in accordance with the latest IEE electrical regulations or the equivalent standards.
- The light source contained in this luminaire shall only be replaced by the manufacturer or his service agent or a similar qualified person.
- Above average concentration of sulfur effects the useful lifetime of the product. E.g: Light color changes from white to blue. Typically in big cities.
- For use in environments where an accumulation of conductive dust on the luminaire may be expected.
- Do not install the luminaire on the location where it is exposed to heavily grease, esp. mineral oil and distillates (petroleum), heavy naphthenic treated with hydrogen.
- This product is not suitable for cold & humid storage areas, especially where obvious temperature gradients are present, such as refrigerating, door, etc.e.g. freezers.
- Do not install the luminaire on locations where it is exposed to direct sunlight. UV radiation will damage the material over time resulting in loss of waterproof sealing and IP66 rating.
- Do not install the luminaire on the location where it is exposed to (animal) grease, oil, esp. cooking or mineral oil and distillates (petroleum), heavy naphthenic treated with hydrogen, or swimming pool applications (with chlorine present), or carwash (due to chemicals and/or pressure).

The servicing of the controlgear in this luminaire should only be undertaken by the manufacturer or their service agent or a similarly skilled person.

©09/2026 Signify Holding.
All rights reserved. This document contains information relating to the product portfolio of Signify which information may be subject to change. No representation or warranty as to the accuracy or completeness of the information included herein is given and any liability for any action in reliance thereon is disclaimed. The information presented in this document is not intended as any commercial offer and does not form part of any quotation or contract. Philips and the Philips Shield Emblem are registered trademarks of Koninklijke Philips N.V.. All other trademarks are owned by Signify Holding or their respective owners.

Signify Holding.
The Netherlands



	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
Driver I peak[A]	24.5	24.5	24.5	38.4	49
Driver Turf [cm]	136	136	136	141	188

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
MCB 10A type B	35	35	35	31	12
MCB 10A type C	22	22	22	13	8
MCB 10A type D	60	60	60	60	60
MCB 16A type B	36	36	36	22	12
MCB 16A type C	60	60	60	60	60
MCB 16A type D	60	60	60	60	60

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
Driver I peak[A]	24.5	24.5	24.5	38.4	49
Driver Turf [cm]	136	136	136	141	188

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
MCB 10A type B	35	35	35	31	12
MCB 10A type C	22	22	22	13	8
MCB 10A type D	60	60	60	60	60
MCB 16A type B	36	36	36	22	12
MCB 16A type C	60	60	60	60	60
MCB 16A type D	60	60	60	60	60

- According to MCB type & through wire cross-section area, choose the minimum number to connect products.

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
2.5 mm²	32	28	21	16	11
1.5 mm²	20	17	13	10	7

- According to MCB type & through wire cross-section area, choose the minimum number to connect products.



	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
Driver I peak[A]	24.5	24.5	24.5	38.4	49
Driver Turf [cm]	136	136	136	141	188

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
MCB 10A type B	35	35	35	31	12
MCB 10A type C	22	22	22	13	8
MCB 10A type D	60	60	60	60	60
MCB 16A type B	36	36	36	22	12
MCB 16A type C	60	60	60	60	60
MCB 16A type D	60	60	60	60	60

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
2.5 mm²	32	28	21	16	11
1.5 mm²	20	17	13	10	7

- According to MCB type & through wire cross-section area, choose the minimum number to connect products.

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
2.5 mm²	30	20	15	12	11
1.5 mm²	20	13	10	8	7

- According to MCB type & through wire cross-section area, choose the minimum number to connect products.



	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
Driver I peak[A]	24.5	24.5	24.5	38.4	49
Driver Turf [cm]	136	136	136	141	188

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
MCB 10A type B	35	35	35	31	12
MCB 10A type C	22	22	22	13	8
MCB 10A type D	60	60	60	60	60
MCB 16A type B	36	36	36	22	12
MCB 16A type C	60	60	60	60	60
MCB 16A type D	60	60	60	60	60

	24_29_35_405 PSU	27_33_39_445 PSU	35_41_51_605 PSU	46_57_69_805 PSU	70_86_100_1205 PSU
2.5 mm²	32	28	21	16	11
1.5 mm²	20	17	13	10