

LED Basic-Tape M 1200



IP
20

24 V DC

20 W

L70/B10 ≥ 50.000 h

LED Basic-Tape M 1200

5000

25

10

4

L	Wattage
500	2,2 W
1000	4,4 W
1500	6,7 W
2000	8,9 W
3000	12,9 W
4000	16,4 W
5000	20,0 W

A

2500

1000 / 2500

6

13

1

50 / 200 / 2500

19

4,5

16

3

Die Anschlussleitung immer am 2. Segment anlöten.
Solder the supply cable on the second segment of the Tape.

B

2500

1000 / 2500

6

13

1

50 / 200 / 2500

19

4,5

16

3

C

2500

1000 / 2500

6

13

1

50 / 200 / 2500

19

4,5

16

3

D

z.B. Einfräseprofil 34 mm
e.g. Milled Profile 34 mm

ø8 mm

LED 24/...W

Montage- und Bedienungsanleitung

Hera LED Linienleuchte Typ LED Basic-Tape M 1200

Bestimmungsgemäße Verwendung

Selbstklebende, flexible LED Streifen. Als Möbelleuchte gemäß VDE 0710 Teil 14/04.82 zum Einbau in Möbel zugelassen.

- Beim Austausch von defekten Teilen dürfen nur Originalteile verwendet werden.
 - Alle Steckverbindungen immer bis zum Anschlag einführen.
 - Polung beachten (Aufdruck auf LED Tape)!
 - Die Clipse sind nach der Verrastung nicht mehr zu öffnen!
 - Die Lichtquelle dieser Leuchte ist nicht ersetzbar; wenn die Lichtquelle ihr Lebensdauerende erreicht hat, ist die gesamte Leuchte zu ersetzen.
 - Die Leuchte nicht demontieren da das Licht der Leuchtdioden das menschliche Auge verletzen kann.
 - Anschluß nur an spezielle LED - Konverter Hera Typ LED 24/...W mit konstanter Ausgangsspannung 24 V DC und einer Ausgangsleistung von max. 100 W, max. 20 W bzw. 10 m pro Anschlussleitung.
 - Die Streifen lassen sich ohne zu löten mit dem Verbindungsclip oder den Leitungen kontaktieren.
 - Werden andere als die angegebenen LED - Konverter eingesetzt, übernimmt Hera keine Gewährleistung.
 - Für trockene, saubere, hochenergetische Oberflächen (keine pulverlackierten Bleche) geeignet. Weitere Verarbeitungshinweise auf der Produktseite unter www.hera-online.de.

erhältliches Zubehör:

- Anschlussleitung LED Tape 1200
- Verbindungsclip LED Tape 1200
- Verbindungsleitung LED Tape 1200

Entsorgen Sie elektrische Geräte nicht im Hausmüll, nutzen Sie die Sammelstellen in Ihrer Gemeinde. Wenn Sie das Gerät durch ein neues ersetzen, ist der Verkäufer gesetzlich verpflichtet, das alte mindestens kostenlos zur Entsorgung entgegenzunehmen.

Nachdruck auch auszugsweise verboten.

Erklärung der Symbole: <http://www.hera-online.de/de/fachliches.html>

Assembly and operating Instructions

Hera LED Linear Luminaire Type LED Basic-Tape M 1200

Intended use

Pressure-sensitive, flexible LED strips. Approved as a furniture luminaire in accordance with VDE 0710 part 14/04.82 for installation in furniture.

- Faulty parts should only be replaced with original parts.
 - Always fully insert all plug connections.
 - Observe the correct polarity (print on LED Tape)!
 - The clip can't be open after the clip is locked together!
 - The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire must be replaced.
 - Do not disassemble the luminaire as the light diode can cause damage to the eyes.
 - Connection only to special LED - Converter Hera Type LED 24/...W with a constant output voltage 24 V DC and an output power of max. 100 W, maximum 20 W or 10 m per supply cable.
 - The Tapes can be reconnected without soldering with the connecting clips or cables.
 - Hera grants no warranty when other LED converters as the prescribed converters are used.
 - Suitable for dry, clean, high-level surfaces (no powder coated sheets).

available accessories:

- supply cable LED Tape 1200
- connecting clip LED Tape 1200
- connecting cable LED Tape 1200

Do not dispose of electrical appliances in household waste, use separate collection facilities. When replacing old appliances with new ones, the retailer is obliged by law to accept to take back your old appliance for disposal free of charge.

Reproduction of this document in whole or part is forbidden.

Explanation of the Symbols: <http://www.hera-online.de/en/technical-information.html>

Hera® Hera GmbH & Co. KG
Dieselstraße 9
32130 Enger / Germany